

VR4K Audiokits

Vandal Resistant 4000 Series Flush & Surface Audiokits



VANDAL
RESISTANT



STANDARD
4+1 AUDIO



Part No.	VR4K-1	VR4K-1S	VR4K-2	VR4K-2S
CONNECTION	STANDARD 4+1 AUDIO			
OUTDOOR STATION	Vandal Resistant 4000 Series			
SPEAKER UNIT MODULE	1 x VR4KAM-1 (136)		1 x VR4KAM-2 (136)	
LEDs	DDA compliant call progress LED's: Yellow (speak), Red (busy) and Green (Open)			
CALL BUTTONS	1		2	
DOOR OPENING	Built-in Lock Relay : C, NC, NO, (max. 24Vac/dc @ 3A)			
CALL TYPE	Electronic Call Tone (with reassurance tones)			
MOUNTING BOX	1 x 4851	1 x 4881	1 x 4851	1 x 4881
RAINSHIELD OPTION*	4871	4891	4871	4891
SIZE	1 module			
MOUNTING	Flush	Surface	Flush	Surface
INDOOR STATION	1 x 3111		2 x 3111	
SERIES	3000 Series Audiophone			
CALL	Electronic Call Tone			
BUTTONS	2: Door Open and Spare Service Button			
CONTROLS	Call tone volume (3 Levels)			
MOUNTING	Surface or deskmount with 3038 desk kit			
POWER SUPPLY UNIT	1 x 520M			
INPUT/OUTPUT	230Vac / 8Vdc (+), 12Vdc (+12), 13Vac (-) with common 0V (-)			
CURRENT RATING	315mA (dc); 1.6A (ac)			
SIZE	8 Modules A Type DIN Box (105x140x65mm)			
MOUNTING	DIN rail or direct wall fixing			

* To be ordered separately

3 WAY UP TO 12 WAY VR4K AUDIOKITS

VR4K-3 up to VR4K-12 flush kits and VR4K-3S up to VR4K-12S surface kits are also available with the appropriate VR4KAM (136) speaker module, VR4KBM-4, VR4KBM-5, VR4KBM-6, VR4KBM-7, VR4KBM-8 or VR4KBM-9 button modules and the appropriate flush (4851, 4852) or surface (4881, 4882) back boxes included. Please note that panel sizes and back box sizes will vary depending on the Audiokit required. Please also note that all kits are supplied with the appropriate number of 3111 audiophones, e.g. a VR4K-6 flush kit will be supplied with 6x 3111 audiophones and so on.

